### University of Pennsylvania Department of Electrical and System Engineering Digital Signal Processing

Midterm	Thursday, March 2	21
	0,	

- 4 Problems with point weightings shown. All 4 problems must be completed.
- Calculators allowed. (non cell phone)
- Closed book = No text allowed. One two-sided  $8.5 \times 11$  cheat sheet allowed.

### Name:

## Grade:

Q1	
Q2	
Q3	
Q4	
Total	

#### TABLE 2.3 FOURIER TRANSFORM PAIRS

Sequence	Fourier Transform	TABLE 2.2         FOURIER TRANSFORM THEOREM	MS
1. δ[n]	1	Sequence	Fourier Transform
2. $\delta[n - n_0]$	$e^{-j\omega n_0}$	x[n]	$X\left(e^{j\omega} ight)$
3. 1 $(-\infty < n < \infty)$	$\sum_{k=1}^{\infty} 2\pi \delta(\omega + 2\pi k)$	<i>y</i> [ <i>n</i> ]	$Y(e^{j\omega})$
	<i>k</i> =−∞	1. $ax[n] + by[n]$	$aX(e^{j\omega})+bY(e^{j\omega})$
4. $a^n u[n]$ (  <i>a</i>   < 1)	$\frac{1}{1-ae^{-j\omega}}$	2. $x[n-n_d]$ ( $n_d$ an integer)	$e^{-j\omega n_d}X(e^{j\omega})$
5[]	1 $\sum_{k=1}^{\infty} -s(k+2k)$	3. $e^{j\omega_0 n} x[n]$	$X(e^{j(\omega-\omega_0)})$
5. <i>u</i> [ <i>n</i> ]	$\frac{1}{1 - e^{-j\omega}} + \sum_{k=-\infty}^{\pi \delta(\omega + 2\pi k)}$	4. $x[-n]$	$X(e^{-j\omega})$ $X^*(e^{j\omega})$ if $r[n]$ real
6. $(n+1)a^n u[n]$ ( a  < 1)	$\frac{1}{(1-ae^{-j\omega})^2}$		
7. $\frac{r^n \sin \omega_p(n+1)}{\sin \omega_p} u[n]  ( r  < 1)$	$\frac{1}{1-2}$	5. <i>nx</i> [ <i>n</i> ]	$j \frac{dX(e^{j\omega})}{d\omega}$
$\sin \omega_p$	$1 - 2r\cos\omega_p e^{-j\omega} + r^2 e^{-j\omega\omega}$	6. $x[n] * y[n]$	$X(e^{j\omega})Y(e^{j\omega})$
8. $\frac{\sin \omega_c n}{\pi n}$	$X\left(e^{j\omega}\right) = \begin{cases} 1, &  \omega  < \omega_{c}, \\ 0, & \omega_{c} <  \omega  \le \pi \end{cases}$	7. $x[n]y[n]$	$\frac{1}{2\pi}\int_{-\pi}^{\pi}X(e^{j\theta})Y(e^{j(\omega-\theta)})d\theta$
9. $x[n] = \begin{cases} 1, & 0 \le n \le M \\ 0, & \text{otherwise} \end{cases}$	$\frac{\sin[\omega(M+1)/2]}{\sin(\omega/2)}e^{-j\omega M/2}$	Parseval's theorem:	$2\pi y = \pi$
10. $e^{j\omega_0 n}$	$\sum_{k=-\infty}^{\infty} 2\pi\delta(\omega-\omega_0+2\pi k)$	$8.\sum_{n=-\infty}^{\infty} x[n] ^2=\frac{1}{2\pi}\int_{-\pi}^{\pi} X(e^{j\omega}) ^2d\omega$	
11. $\cos(\omega_0 n + \phi)$	$\sum_{k=-\infty}^{\infty} [\pi e^{j\phi} \delta(\omega - \omega_0 + 2\pi k) + \pi e^{-j\phi} \delta(\omega + \omega_0 + 2\pi k)]$	9. $\sum_{n=-\infty}^{\infty} x[n]y^*[n] = \frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{j\omega})Y^*(e^{j\omega})d\omega$	
TABLE 3.1         SOME COMMON z-TRANSFORM	PAIRS		
Sequence Tr	ransform ROC		
1. δ[n] 1	All z		
2. $u[n] = \frac{1}{1}$	z  > 1	TARIES 2 SOME 7-TRANSFORM PROPERTIES	

1. $o[n]$	1						
2. <i>u</i> [ <i>n</i> ]	$\frac{1}{1-z^{-1}}$	z  > 1	TABLE 3.2	SOME z-TRAN	ISFORM PROPERTIES		
3. $-u[-n-1]$	$\frac{1}{1-z^{-1}}$	z  < 1	Property Number	Section Reference	Sequence	Transform	ROC
4. $\delta[n-m]$	$z^{-m}$	All z except 0 (if $m > 0$ ) or $\infty$ (if $m < 0$ )			x[n]	X(z)	R <sub>x</sub>
5. $a^{n}u[n]$	$\frac{1}{1-az^{-1}}$	z  >  a			$x_1[n]$	$X_1(z)$	$R_{x_1}$
6. $-a^n u[-n-1]$	$\frac{1}{1}$	z  <  a			$x_2[n]$	$X_2(z)$	$R_{x_2}$
	$1 - az^{-1}$		1	3.4.1	$ax_1[n] + bx_2[n]$	$aX_1(z) + bX_2(z)$	Contains $R_{x_1} \cap R_{x_2}$
7. $na^n u[n]$	$\frac{az}{(1-az^{-1})^2}$	z  >  a	2	3.4.2	$x[n-n_0]$	$z^{-n_0}X(z)$	$R_x$ , except for the possible
8. $-na^{n}u[-n-1]$	$\frac{az^{-1}}{(1-az^{-1})^2}$	z  <  a					the origin or $\infty$
0	$1 - \cos(\omega_0) z^{-1}$		3	3.4.3	$z_0^n x[n]$	$X(z/z_0)$	$ z_0 R_x$
9. $\cos(\omega_0 n)u[n]$	$\overline{1-2\cos(\omega_0)z^{-1}+z^{-2}}$	z  > 1	4	311	" ×["]	dX(z)	D
$10 \sin(\omega n) u[n]$	$\sin(\omega_0)z^{-1}$	z  > 1	5	3.4.4	nx[n]	$\frac{-z}{dz}$	R <sub>X</sub> P
10. Shi(@()#)#[#]	$1 - 2\cos(\omega_0)z^{-1} + z^{-2}$		5	5.4.5	x [n]	A (2)	Kχ
11. $r^n \cos(\omega_0 n) u[n]$	$\frac{1 - r\cos(\omega_0)z^{-1}}{1 - 2r\cos(\omega_0)z^{-1} + r^2z^{-2}}$	z  > r	6		$\mathcal{R}e\{x[n]\}$	$\frac{1}{2}[X(z) + X^*(z^*)]$	Contains $R_x$
12. $r^n \sin(\omega_0 n) u[n]$	$\frac{r\sin(\omega_0)z^{-1}}{1-2r\cos(\omega_0)z^{-1}+r^2z^{-2}}$	z  > r	7		$\mathcal{I}m\{x[n]\}$	$\frac{1}{2i}[X(z) - X^*(z^*)]$	Contains $R_x$
$a^n, 0 \le n \le N - 1,$	$1 - a^N z^{-N}$		8	3.4.6	$x^{*}[-n]$	$\bar{X}^{*}(1/z^{*})$	$1/R_x$
13. $\{0, \text{ otherwise } \}$	$1 - az^{-1}$	z  > 0	9	3.4.7	$x_1[n] \ast x_2[n]$	$X_1(z)X_2(z)$	Contains $R_{x_1} \cap R_{x_2}$

## Trigonometric Identity:

$$e^{j\Theta} = \cos(\Theta) + j\sin(\Theta)$$

Geometric Series:

$$\sum_{n=0}^{N} r^n = \frac{1-r^{N+1}}{1-r}$$
$$\sum_{n=0}^{\infty} r^n = \frac{1}{1-r}, |r| < 1$$

# **DTFT Equations:**

$$X(e^{j\omega}) = \sum_{k=-\infty}^{\infty} x[k]e^{-j\omega k}$$
$$x[n] = \frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{j\omega})e^{j\omega n} d\omega$$

# Z-Transform Equations:

$$X(z) = \sum_{n=-\infty}^{\infty} x[n] z^{-n}$$
$$x[n] = \frac{1}{2\pi j} \oint_{C} X(z) z^{n-1} dz$$

Upsampling/Downsampling:

Upsampling by L ( $\uparrow$ L):  $X_{up} = X(e^{j\omega L})$ Downsampling by M ( $\downarrow$ M):  $X_{down} = \frac{1}{M} \sum_{i=0}^{M-1} X(e^{j(\frac{\omega}{M} - \frac{2\pi}{M}i)})$ 

Interchange Identities:

$$\begin{array}{rcl} x[n] & & & & & \\ & & & \\ & & & \\$$

1. (20 points) Consider the system shown in Figure 1 for discrete-time processing of the continuous-time input signal  $g_c(t)$ . The input signal  $g_c(t)$  is of the form  $g_c(t) = f_c(t) + e_c(t)$ . where the Fourier transforms of  $f_c(t)$  and  $e_c(t)$  are shown in Figure 2. Since the input signal is not bandlimited, a continuous-time antialiasing filter  $H_{aa}(j\Omega)$  is used. The frequency response for  $H_{aa}(j\Omega)$  is shown in Figure 3. Assume the C/D and D/C blocks are ideal as in class. Ideal means that the D/C converter contains an ideal lowpass reconstruction filter with a bandwidth of  $\pi/T$  and a gain of T.



(a) If the sampling rate is  $\Omega_S = 1600\pi$ , determine  $H(e^{j\omega})$ , the frequency response of the discrete-time system, so that the output is  $y_c(t) = f_c(t)$ .

(b) It turns out that since we are only interested in obtaining  $f_c(t)$  at the output, we can use a lower sampling rate than  $\Omega_S = 1600\pi$  while still using the antialiasing filter in Figure 3. Determine the minimum value of  $\Omega_S$  such that  $y_c(t) = f_c(t)$ ? Determine  $H(e^{j\omega})$  for this new choice of  $\Omega_S$ .

2. (30 points) The discrete-time filtering system shown in Figure 4 comprises a C/D converter sampling at rate  $f_1 = 2000Hz$ , a filter with frequency response  $H(e^{j\omega})$ , a resampler that resamples at a rate of D: U (downsample by D, and upsample by U) and an ideal D/C converter at rate  $f_2$ . Ideal means that the D/C converter contains an ideal lowpass reconstruction filter with a bandwidth of  $\pi f_2$  and a gain of  $1/f_2$ . The spectrum of the input,  $X(j\Omega)$ , and frequency response,  $H(e^{j\omega})$ , are shown in Figure 5.



- (a) Plot the spectra  $X(e^{j\omega})$  and  $Y(e^{j\omega})$ . Label all axes and relevant features.
- (b) Given  $f_2 = 1000Hz$ , U = 1, and D = 2, plot the spectra  $Z(e^{j\omega})$  and  $Z(j\Omega)$ . Label all axes and relevant features.
- (c) Given  $f_2 = 4000 Hz$ , U = 2, and D = 1, plot the spectra  $Z(e^{j\omega})$  and  $Z(j\Omega)$ . Label all axes and relevant features.

ESE5310

(You may continue the problem on this almost blank page.)

3. (30 points) A stable system is shown below, comprising a cascade of two LTI discretetime filters such that y[n] = x[n].



The first filter has an unknown impulse response, h[n]. The second filter is defined by the difference equation:

$$y[n] = v[n] - \frac{3}{4}v[n-1] + \frac{1}{8}v[n-2]$$
(1)

For each filter G(z) and H(z) in the combined system:

- (a) Find the transfer function and impulse response.
- (b) Plot the filter pole-zero plot and indicate the ROC.
- (c) Indicate if the filter is all-pass, min-phase, or neither. Explain your reasoning.

ESE5310

(You may continue the problem on this almost blank page.)

4. (20 points) For each H(z) in the table below, select the matching magnitude response from the magnitude plots M1-M6 also shown below. It is possible that some pictures may apply to more than one system, and some pictures will not apply to any system. If none of the pictures is possible, write none.

H(z)	Magnitude Plot
z-2	
$\frac{3}{2}\frac{1+jz}{z-j}$	
$2(z+\frac{1}{2})$	
$\frac{3}{2}\frac{z+1}{2z-1}$	
$\frac{3}{2}(z-1)$	
z+2	

