

ESE 531: Digital Signal Processing

Lec 12: February 22, 2018
Frequency Response of LTI Systems

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley



Lecture Outline

- Frequency Response of LTI Systems
 - Magnitude Response
 - Simple Filters
 - Phase Response
 - Group Delay
 - Example: Zero on Real Axis

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

2

Frequency Response of LTI System

- LTI Systems are uniquely determined by their impulse response

$$y[n] = \sum_{k=-\infty}^{\infty} x[k] h[n-k] = x[k] * h[k]$$

- We can write the input-output relation also in the z-domain

$$Y(z) = H(z)X(z)$$

- Or we can define an LTI system with its frequency response

$$Y(e^{j\omega}) = H(e^{j\omega})X(e^{j\omega})$$

- $H(e^{j\omega})$ defines magnitude and phase change at each frequency

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

3

Frequency Response of LTI System

$$Y(e^{j\omega}) = H(e^{j\omega})X(e^{j\omega})$$

- We can define a magnitude response

$$|Y(e^{j\omega})| = |H(e^{j\omega})||X(e^{j\omega})|$$

- And a phase response

$$\angle Y(e^{j\omega}) = \angle H(e^{j\omega}) + \angle X(e^{j\omega})$$

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

4

Phase Response

- Limit the range of the phase response

$$-\pi < \text{ARG}[H(e^{j\omega})] \leq \pi.$$


Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

5

Phase Response

- Limit the range of the phase response

$$-\pi < \text{ARG}[H(e^{j\omega})] \leq \pi.$$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

6

Group Delay

- General phase response at a given frequency can be characterized with group delay, which is related to phase

$$\text{grd}[H(e^{j\omega})] = -\frac{d}{d\omega}\{\arg[H(e^{j\omega})]\}$$

- More later...

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

7

Linear Difference Equations

$$\sum_{k=0}^N a_k y[n-k] = \sum_{k=0}^M b_k x[n-k]$$

Example: $y[n] = x[n] + 0.1y[n-1]$

$$H(z) = \frac{b_0 + b_1 z^{-1} + \dots + b_M z^{-M}}{a_0 + a_1 z^{-1} + \dots + a_N z^{-N}} = \frac{b_0 \prod_{k=1}^M (1 - c_k z^{-1})}{a_0 \prod_{k=1}^N (1 - d_k z^{-1})}$$

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

8

Magnitude Response

Magnitude of products is product of magnitudes

$$|H(e^{j\omega})| = \left| \frac{b_0}{a_0} \right| \cdot \frac{\prod_{k=0}^M |1 - c_k e^{-j\omega}|}{\prod_{k=0}^N |1 - d_k e^{-j\omega}|}$$

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

9

Magnitude Response

Magnitude of products is product of magnitudes

$$|H(e^{j\omega})| = \left| \frac{b_0}{a_0} \right| \cdot \frac{\prod_{k=0}^M |1 - c_k e^{-j\omega}|}{\prod_{k=0}^N |1 - d_k e^{-j\omega}|}$$

Consider one of the poles:

$$|1 - d_k e^{-j\omega}| = |e^{+j\omega} - d_k| = |v_1|$$

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

10


Magnitude Response

Magnitude of products is product of magnitudes

$$|H(e^{j\omega})| = \left| \frac{b_0}{a_0} \right| \cdot \frac{\prod_{k=0}^M |1 - c_k e^{-j\omega}|}{\prod_{k=0}^N |1 - d_k e^{-j\omega}|}$$

Consider one of the poles:

$$|1 - d_k e^{-j\omega}| = |e^{+j\omega} - d_k| = |v_1|$$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

11


Magnitude Response

Magnitude of products is product of magnitudes

$$|H(e^{j\omega})| = \left| \frac{b_0}{a_0} \right| \cdot \frac{\prod_{k=0}^M |1 - c_k e^{-j\omega}|}{\prod_{k=0}^N |1 - d_k e^{-j\omega}|}$$

Consider one of the poles:

$$|1 - d_k e^{-j\omega}| = |e^{+j\omega} - d_k| = |v_1|$$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

12


Magnitude Response

Magnitude of products is product of magnitudes

$$|H(e^{j\omega})| = \left| \frac{b_0}{a_0} \right| \cdot \frac{\prod_{k=0}^M |1 - c_k e^{-j\omega}|}{\prod_{k=0}^N |1 - d_k e^{-j\omega}|}$$

Consider one of the poles:

$$|1 - d_k e^{-j\omega}| = |e^{+j\omega} - d_k| = |v_1|$$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

13


Magnitude Response

Magnitude of products is product of magnitudes

$$|H(e^{j\omega})| = \left| \frac{b_0}{a_0} \right| \cdot \frac{\prod_{k=0}^M |1 - c_k e^{-j\omega}|}{\prod_{k=0}^N |1 - d_k e^{-j\omega}|}$$

Consider one of the poles:

$$|1 - d_k e^{-j\omega}| = |e^{+j\omega} - d_k| = |v_1|$$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

14


Magnitude Response

Magnitude of products is product of magnitudes

$$|H(e^{j\omega})| = \left| \frac{b_0}{a_0} \right| \cdot \frac{\prod_{k=0}^M |1 - c_k e^{-j\omega}|}{\prod_{k=0}^N |1 - d_k e^{-j\omega}|}$$

Consider one of the poles:

$$|1 - d_k e^{-j\omega}| = |e^{+j\omega} - d_k| = |v_1|$$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

15


Magnitude Response

Magnitude of products is product of magnitudes

$$|H(e^{j\omega})| = \left| \frac{b_0}{a_0} \right| \cdot \frac{\prod_{k=0}^M |1 - c_k e^{-j\omega}|}{\prod_{k=0}^N |1 - d_k e^{-j\omega}|}$$

Consider one of the poles:

$$|1 - d_k e^{-j\omega}| = |e^{+j\omega} - d_k| = |v_1|$$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

16


Magnitude Response

Magnitude of products is product of magnitudes

$$|H(e^{j\omega})| = \left| \frac{b_0}{a_0} \right| \cdot \frac{\prod_{k=0}^M |1 - c_k e^{-j\omega}|}{\prod_{k=0}^N |1 - d_k e^{-j\omega}|}$$

Consider one of the poles:

$$|1 - d_k e^{-j\omega}| = |e^{+j\omega} - d_k| = |v_1|$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

17

Magnitude Response Example

$$H(z) = 0.05 \frac{1 + z^{-1}}{1 - 0.9z^{-1}}$$

$$|H(z)| = 0.05 \frac{|v_2|}{|v_1|}$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

18

Magnitude Response Example

$$H(z) = 0.05 \frac{1 + z^{-1}}{1 - 0.9z^{-1}}$$

$$|H(z)| = 0.05 \frac{|v_2|}{|v_1|}$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

19

Magnitude Response Example

$$H(z) = 0.05 \frac{1 + z^{-1}}{1 - 0.9z^{-1}}$$

$$|H(z)| = 0.05 \frac{|v_2|}{|v_1|}$$





Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

20

Magnitude Response Example

$$H(z) = 0.05 \frac{1 + z^{-1}}{1 - 0.9z^{-1}}$$

$$|H(z)| = 0.05 \frac{|v_2|}{|v_1|}$$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

21

Simple Low Pass Filter


$$H_{LP}(z) = \frac{1 - \alpha}{2} \frac{1 + z^{-1}}{1 - \alpha z^{-1}} \quad |\alpha| < 1$$

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

22

Simple Low Pass Filter

$$H_{LP}(z) = \frac{1 - \alpha}{2} \frac{1 + z^{-1}}{1 - \alpha z^{-1}} \quad |\alpha| < 1$$



ω_c is the 3dB cutoff frequency $\alpha = \frac{1 - \sin(\omega_c)}{\cos(\omega_c)}$

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

23

Simple High Pass Filter


$$H_{HP}(z) = \frac{1 + \alpha}{2} \frac{1 - z^{-1}}{1 + \alpha z^{-1}} \quad |\alpha| < 1$$

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

24

Simple High Pass Filter

$$H_{HP}(z) = \frac{1+\alpha}{2} \frac{1-z^{-1}}{1+\alpha z^{-1}} \quad |\alpha| < 1$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

25

Simple High Pass Filter

$$H_{HP}(z) = \frac{1+\alpha}{2} \frac{1-z^{-1}}{1+\alpha z^{-1}} \quad |\alpha| < 1$$



ω_c is the 3dB cutoff frequency $\alpha = \frac{1 - \sin(\omega_c)}{\cos(\omega_c)}$

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

26

Simple Band-Stop (Notch) Filter

$$H_{BS}(z) = \frac{1+\alpha}{2} \frac{1-2\beta z^{-1}+z^{-2}}{1-\beta(1+\alpha)z^{-1}+\alpha z^{-2}} \quad \begin{matrix} |\alpha| < 1 \\ |\beta| < 1 \end{matrix}$$

Note: $1-2\beta z^{-1}+z^{-2} = (1-e^{j\omega_0}z^{-1})(1-e^{-j\omega_0}z^{-1})$
 $\cos(\omega_0) = \beta$


Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

27

Simple Band-Stop (Notch) Filter

$$H_{BS}(z) = \frac{1+\alpha}{2} \frac{1-2\beta z^{-1}+z^{-2}}{1-\beta(1+\alpha)z^{-1}+\alpha z^{-2}} \quad \begin{matrix} |\alpha| < 1 \\ |\beta| < 1 \end{matrix}$$

Note: $1-2\beta z^{-1}+z^{-2} = (1-e^{j\omega_0}z^{-1})(1-e^{-j\omega_0}z^{-1})$
 $\cos(\omega_0) = \beta$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

28

Simple Band-Stop (Notch) Filter

$$H_{BS}(z) = \frac{1+\alpha}{2} \frac{1-2\beta z^{-1}+z^{-2}}{1-\beta(1+\alpha)z^{-1}+\alpha z^{-2}} \quad \begin{matrix} |\alpha| < 1 \\ |\beta| < 1 \end{matrix}$$

Note: $1-2\beta z^{-1}+z^{-2} = (1-e^{j\omega_0}z^{-1})(1-e^{-j\omega_0}z^{-1})$
 $\cos(\omega_0) = \beta$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley


29

Simple Band-Stop (Notch) Filter

$$H_{BS}(z) = \frac{1+\alpha}{2} \frac{1-2\beta z^{-1}+z^{-2}}{1-\beta(1+\alpha)z^{-1}+\alpha z^{-2}} \quad \begin{matrix} |\alpha| < 1 \\ |\beta| < 1 \end{matrix}$$

Note:

$$H_{BS}(\mp 1) = \frac{1+\alpha}{2} \frac{2 \pm 2\beta}{(1+\alpha)(1 \pm \beta)} = 1$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

30

Simple Band-Stop (Notch) Filter

$$H_{BS}(z) = \frac{1+\alpha}{2} \frac{1-2\beta z^{-1}+z^{-2}}{1-\beta(1+\alpha)z^{-1}+\alpha z^{-2}} \quad \begin{matrix} |\alpha| < 1 \\ |\beta| < 1 \end{matrix}$$

Note: As $\alpha \rightarrow 1$ poles approach zeros
 $H_{BS}(\mp 1) = \frac{1+\alpha}{2} \frac{2 \pm 2\beta}{(1+\alpha)(1 \pm \beta)} = 1$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

31

Simple Band-Pass Filter


$$H_{BP}(z) = \frac{1-\alpha}{2} \frac{1-z^{-2}}{1-\beta(1+\alpha)z^{-1}+\alpha z^{-2}} \quad \begin{matrix} |\alpha| < 1 \\ |\beta| < 1 \end{matrix}$$

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

32

Simple Band-Pass Filter

$$H_{BP}(z) = \frac{1-\alpha}{2} \frac{1-z^{-2}}{1-\beta(1+\alpha)z^{-1}+\alpha z^{-2}} \quad \begin{matrix} |\alpha| < 1 \\ |\beta| < 1 \end{matrix}$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

33

Simple Band-Pass Filter

$$H_{BP}(z) = \frac{1-\alpha}{2} \frac{1-z^{-2}}{1-\beta(1+\alpha)z^{-1}+\alpha z^{-2}} \quad \begin{matrix} |\alpha| < 1 \\ |\beta| < 1 \end{matrix}$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

34

Simple Band-Pass Filter

$$H_{BP}(z) = \frac{1-\alpha}{2} \frac{1-z^{-2}}{1-\beta(1+\alpha)z^{-1}+\alpha z^{-2}} \quad \begin{matrix} |\alpha| < 1 \\ |\beta| < 1 \end{matrix}$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

35

Phase Response

Limit the range of the phase response

$$-\pi < \text{ARG}[H(e^{j\omega})] \leq \pi.$$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

36


Phase Response Example

$$H(e^{j\omega}) = e^{j\omega n_d} \leftrightarrow h[n] = \delta[n - n_d]$$

$$|H(e^{j\omega})| = 1$$

$$\arg[H(e^{j\omega})] = -\omega n_d$$

ARG is the wrapped phase
arg is the unwrapped phase




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

37

Group Delay

- General phase response at a given frequency can be characterized with group delay, which is related to phase

$$\text{grd}[H(e^{j\omega})] = -\frac{d}{d\omega} \{\arg[H(e^{j\omega})]\}$$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

38


Phase Response Example

$$H(e^{j\omega}) = e^{j\omega n_d} \leftrightarrow h[n] = \delta[n - n_d]$$

$$|H(e^{j\omega})| = 1$$

$$\arg[H(e^{j\omega})] = -\omega n_d$$

ARG is the wrapped phase
arg is the unwrapped phase



$$\text{grd}[H(e^{j\omega})] = -\frac{d}{d\omega} \{\arg[H(e^{j\omega})]\}$$

For linear phase system, group delay is n_d


Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

39

Group Delay

- General phase response at a given frequency can be characterized with group delay, which is related to phase

$$\text{grd}[H(e^{j\omega})] = -\frac{d}{d\omega} \{\arg[H(e^{j\omega})]\}$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

40

Group Delay

$$\text{grd}[H(e^{j\omega})] = -\frac{d}{d\omega} \{\arg[H(e^{j\omega})]\}$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

41

Group Delay

$$\text{grd}[H(e^{j\omega})] = -\frac{d}{d\omega} \{\arg[H(e^{j\omega})]\}$$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

42

Group Delay Math

$$H(z) = \frac{b_0 \prod_{k=1}^M (1 - c_k z^{-1})}{a_0 \prod_{k=1}^N (1 - d_k z^{-1})} \quad H(e^{j\omega}) = \frac{b_0 \prod_{k=1}^M (1 - c_k e^{-j\omega})}{a_0 \prod_{k=1}^N (1 - d_k e^{-j\omega})}$$

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

43

Group Delay Math

$$H(z) = \frac{b_0 \prod_{k=1}^M (1 - c_k z^{-1})}{a_0 \prod_{k=1}^N (1 - d_k z^{-1})} \quad H(e^{j\omega}) = \frac{b_0 \prod_{k=1}^M (1 - c_k e^{-j\omega})}{a_0 \prod_{k=1}^N (1 - d_k e^{-j\omega})}$$

arg of products is sum of args

$$\arg[H(e^{j\omega})] = \sum_{k=1}^M \arg[1 - c_k e^{-j\omega}] - \sum_{k=1}^N \arg[1 - d_k e^{-j\omega}]$$

$$\text{grd}[H(e^{j\omega})] = \sum_{k=1}^M \text{grd}[1 - c_k e^{-j\omega}] - \sum_{k=1}^N \text{grd}[1 - d_k e^{-j\omega}]$$

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

44

Group Delay Math

$$\text{grd}[H(e^{j\omega})] = \sum_{k=1}^M \text{grd}[1 - c_k e^{-j\omega}] - \sum_{k=1}^N \text{grd}[1 - d_k e^{-j\omega}]$$

Look at each factor:

$$\arg[1 - r e^{j\theta} e^{-j\omega}] = \tan^{-1} \left(\frac{r \sin(\omega - \theta)}{1 - r \cos(\omega - \theta)} \right)$$

$$\text{grd}[1 - r e^{j\theta} e^{-j\omega}] = \frac{r^2 - r \cos(\omega - \theta)}{|1 - r e^{j\theta} e^{-j\omega}|^2}$$


Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

45

Example: Zero on Real Axis

Geometric Interpretation for ($\theta = 0$)

$$\arg[1 - r e^{-j\omega}]$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

46

Example: Zero on Real Axis

Geometric Interpretation for ($\theta = 0$)

$$\arg[1 - r e^{-j\omega}] = \arg[(e^{j\omega} - r) e^{-j\omega}] = \underbrace{\arg[e^{j\omega} - r]}_{\varphi} - \underbrace{\arg[e^{j\omega}]}_{\omega}$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

47

Example: Zero on Real Axis

Geometric Interpretation for ($\theta = 0$)

$$\arg[1 - r e^{-j\omega}] = \arg[(e^{j\omega} - r) e^{-j\omega}] = \underbrace{\arg[e^{j\omega} - r]}_{\varphi} - \underbrace{\arg[e^{j\omega}]}_{\omega}$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

48

Example: Zero on Real Axis

- Geometric Interpretation for ($\theta = 0$)

$$\arg[1 - re^{-j\omega}] = \arg[(e^{j\omega} - r)e^{-j\omega}] = \underbrace{\arg[e^{j\omega} - r]}_{\varphi} - \underbrace{\arg[e^{-j\omega}]}_{\omega}$$




Penn ESE 531 Spring 2018 - Khanna

49

Example: Zero on Real Axis

- Geometric Interpretation for ($\theta = 0$)

$$\arg[1 - re^{-j\omega}] = \arg[(e^{j\omega} - r)e^{-j\omega}] = \underbrace{\arg[e^{j\omega} - r]}_{\varphi} - \underbrace{\arg[e^{-j\omega}]}_{\omega}$$





Penn ESE 531 Spring 2018 - Khanna

50

Example: Zero on Real Axis

- Geometric Interpretation for ($\theta = 0$)

$$\arg[1 - re^{-j\omega}] = \arg[(e^{j\omega} - r)e^{-j\omega}] = \underbrace{\arg[e^{j\omega} - r]}_{\varphi} - \underbrace{\arg[e^{-j\omega}]}_{\omega}$$



Penn ESE 531 Spring 2018 - Khanna



51

Example: Zero on Real Axis

- Geometric Interpretation for ($\theta = 0$)

$$\arg[1 - re^{-j\omega}] = \arg[(e^{j\omega} - r)e^{-j\omega}] = \underbrace{\arg[e^{j\omega} - r]}_{\varphi} - \underbrace{\arg[e^{-j\omega}]}_{\omega}$$

$\omega = 0$





Penn ESE 531 Spring 2018 - Khanna
Adapted from M. Lustig, EECS Berkeley

52

Example: Zero on Real Axis

- Geometric Interpretation for ($\theta = 0$)

$$\arg[1 - re^{-j\omega}] = \arg[(e^{j\omega} - r)e^{-j\omega}] = \underbrace{\arg[e^{j\omega} - r]}_{\varphi} - \underbrace{\arg[e^{-j\omega}]}_{\omega}$$





Penn ESE 531 Spring 2018 - Khanna
Adapted from M. Lustig, EECS Berkeley

53

Example: Zero on Real Axis

- Geometric Interpretation for ($\theta = 0$)

$$\arg[1 - re^{-j\omega}] = \arg[(e^{j\omega} - r)e^{-j\omega}] = \underbrace{\arg[e^{j\omega} - r]}_{\varphi} - \underbrace{\arg[e^{-j\omega}]}_{\omega}$$




Penn ESE 531 Spring 2018 - Khanna
Adapted from M. Lustig, EECS Berkeley

54

Example: Zero on Real Axis

- Geometric Interpretation for ($\theta = 0$)

$$\arg[1 - re^{-j\omega}] = \arg[(e^{j\omega} - r)e^{-j\omega}] = \underbrace{\arg[e^{j\omega} - r]}_{\varphi} - \underbrace{\arg[e^{-j\omega}]}_{\omega}$$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

55

Example: Zero on Real Axis

- Geometric Interpretation for ($\theta = 0$)

$$\arg[1 - re^{-j\omega}] = \arg[(e^{j\omega} - r)e^{-j\omega}] = \underbrace{\arg[e^{j\omega} - r]}_{\varphi} - \underbrace{\arg[e^{-j\omega}]}_{\omega}$$



Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

56

Group Delay Math

$$\text{grd}[H(e^{j\omega})] = \sum_{k=1}^M \text{grd}[1 - c_k e^{-j\omega}] - \sum_{k=1}^N \text{grd}[1 - d_k e^{-j\omega}]$$

- Look at each factor:

$$\arg[1 - re^{j\theta} e^{-j\omega}] = \tan^{-1} \left(\frac{r \sin(\omega - \theta)}{1 - r \cos(\omega - \theta)} \right)$$


$$\text{grd}[1 - re^{j\theta} e^{-j\omega}] = \frac{r^2 - r \cos(\omega - \theta)}{|1 - re^{j\theta} e^{-j\omega}|^2}$$

Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

57

Example: Zero on Real Axis

- For $\theta \neq 0$




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

58

Example: Zero on Real Axis

- Magnitude Response




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

59

Example: Zero on Real Axis

- For $\theta = \pi$, how does zero location effect magnitude, phase and group delay?




Penn ESE 531 Spring 2018 – Khanna
Adapted from M. Lustig, EECS Berkeley

60

Example: Zero on Real Axis

- For $\theta = \pi$, how does zero location effect magnitude, **phase** and group delay?




Penn ESE 531 Spring 2018 - Khanna
Adapted from M. Lustig, EECS Berkeley

61

Example: Zero on Real Axis

- For $\theta = \pi$, how does zero location effect magnitude, phase and **group delay**?




Penn ESE 531 Spring 2018 - Khanna
Adapted from M. Lustig, EECS Berkeley

62

2nd Order IIR with Complex Poles

$$H(z) = \frac{1}{(1 - re^{j\theta}z^{-1})(1 - re^{-j\theta}z^{-1})}$$




Penn ESE 531 Spring 2018 - Khanna

63

2nd Order IIR with Complex Poles

$$H(z) = \frac{1}{(1 - re^{j\theta}z^{-1})(1 - re^{-j\theta}z^{-1})}$$




Penn ESE 531 Spring 2018 - Khanna

64

3rd Order IIR Example

$$H(z) = \frac{0.05634(1 + z^{-1})(1 - 1.0166z^{-1} + z^{-2})}{(1 - 0.683z^{-1})(1 - 1.4461z^{-1} + 0.7957z^{-2})}$$




Penn ESE 531 Spring 2018 - Khanna

65

3rd Order IIR Example

$$H(z) = \frac{0.05634(1 + z^{-1})(1 - 1.0166z^{-1} + z^{-2})}{(1 - 0.683z^{-1})(1 - 1.4461z^{-1} + 0.7957z^{-2})}$$






Penn ESE 531 Spring 2018 - Khanna

66

3rd Order IIR Example

$$H(z) = \frac{0.05634(1 + z^{-1})(1 - 1.0166z^{-1} + z^{-2})}{(1 - 0.683z^{-1})(1 - 1.4461z^{-1} + 0.7957z^{-2})}$$






Penn ESE 531 Spring 2018 - Khanna

67

3rd Order IIR Example

$$H(z) = \frac{0.05634(1 + z^{-1})(1 - 1.0166z^{-1} + z^{-2})}{(1 - 0.683z^{-1})(1 - 1.4461z^{-1} + 0.7957z^{-2})}$$



Penn ESE 531 Spring 2018 - Khanna

68

Big Ideas

- Frequency Response of LTI Systems
 - Magnitude Response
 - Simple Filters
 - Phase Response
 - Group Delay
 - Example: Zero on Real Axis

Penn ESE 531 Spring 2018 - Khanna
Adapted from M. Lustig, EECS Berkeley

69

Admin

- HW 5
 - Due Friday 2/23
- Homework solutions to be posted soon...

Penn ESE 531 Spring 2018 - Khanna

70